

# PRESSURE VS TORQUE CONVERSION CHART

## TITAN LP SERIES TOOLS

|                  | LP 2             | LP 4 | LP 8 | LP 16 | LP 32 |
|------------------|------------------|------|------|-------|-------|
| PUMP PSI Setting | Torque - Ft. Lbs |      |      |       |       |
| 1500             | 268              | 568  | 1075 | 2360  | 5250  |
| 1600             | 286              | 606  | 1146 | 2518  | 5600  |
| 1800             | 322              | 682  | 1290 | 2832  | 6300  |
| 2000             | 360              | 758  | 1488 | 3174  | 7000  |
| 2200             | 396              | 833  | 1637 | 3491  | 7700  |
| 2400             | 431              | 909  | 1785 | 3808  | 8400  |
| 2600             | 467              | 985  | 1934 | 4126  | 9100  |
| 2800             | 503              | 1061 | 2083 | 4443  | 9800  |
| 3000             | 541              | 1136 | 2289 | 4820  | 10500 |
| 3200             | 577              | 1212 | 2442 | 5142  | 11200 |
| 3400             | 614              | 1288 | 2594 | 5463  | 11900 |
| 3600             | 650              | 1364 | 2747 | 5784  | 12600 |
| 3800             | 686              | 1439 | 2899 | 6106  | 13300 |
| 4000             | 724              | 1515 | 3028 | 6475  | 14000 |
| 4200             | 760              | 1591 | 3180 | 6799  | 14700 |
| 4400             | 796              | 1667 | 3331 | 7123  | 15400 |
| 4600             | 833              | 1742 | 3483 | 7447  | 16100 |
| 4800             | 869              | 1818 | 3634 | 7770  | 16800 |
| 5000             | 904              | 1894 | 3878 | 8156  | 17500 |
| 5200             | 940              | 1970 | 4033 | 8482  | 18200 |
| 5400             | 976              | 2045 | 4188 | 8808  | 18900 |
| 5600             | 1013             | 2121 | 4343 | 9134  | 19600 |
| 5800             | 1049             | 2197 | 4498 | 9460  | 20300 |
| 6000             | 1087             | 2273 | 4704 | 9789  | 21000 |
| 6200             | 1123             | 2348 | 4859 | 10116 | 21700 |
| 6400             | 1159             | 2424 | 5017 | 10442 | 22400 |
| 6600             | 1196             | 2500 | 5174 | 10768 | 23100 |
| 6800             | 1232             | 2576 | 5331 | 11095 | 23800 |
| 7000             | 1271             | 2652 | 5545 | 11504 | 24500 |
| 7200             | 1307             | 2727 | 2704 | 11833 | 25200 |
| 7400             | 1343             | 2803 | 5862 | 12162 | 25900 |
| 7600             | 1380             | 2879 | 6021 | 12490 | 26600 |
| 7800             | 1416             | 2955 | 6179 | 12819 | 27300 |
| 8000             | 1459             | 3030 | 6364 | 13046 | 28000 |
| 8200             | 1496             | 3106 | 6523 | 13372 | 28700 |
| 8400             | 1532             | 3182 | 6682 | 13698 | 29400 |
| 8600             | 1568             | 3258 | 6841 | 14024 | 30100 |
| 8800             | 1605             | 3333 | 7000 | 14350 | 30800 |
| 9000             | 1640             | 3409 | 7163 | 14700 | 31500 |
| 9200             | 1676             | 3485 | 7322 | 15027 | 32200 |
| 9400             | 1713             | 3561 | 7481 | 15353 | 32900 |
| 9600             | 1749             | 3636 | 7641 | 15680 | 33600 |
| 9800             | 1785             | 3712 | 7800 | 16007 | 34300 |
| 10000            | 1826             | 3788 | 8024 | 16231 | 35000 |

Calibrated & Ready to Use • Powerful • Compact • Accurate • Durable • Faster • Light Weight • Efficient

### Accessories for the LP-Series Tool

1. ALCO Extended Reaction Arm  
2. Reaction Arms

3. Hex & 12 pt. Step-Down Sleeves  
4. Stack Sockets

5. Square Drive Adapter  
6. Hex Stock